

Please download the latest datasheet of BLM18BA220SN1# from the official website of Murata Manufacturing

https://www.murata.com/en-global/products/productdetail?partno=BLM18BA220SN1%23

### BLM18BA220SN1#

"#" indicates a package specification code.

Note: This datasheet may be out of date






< List of part numbers with package codes >

REACH

BLM18BA220SN1B BLM18BA220SN1D BLM18BA220SN1J



#### Appearance & Shape





The chip ferrite beads BLM series is designed to work nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM\_B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance.



Other Usage	For general
-------------	-------------



## **Packaging Information**

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=BLM18BA220SN1%23

 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM18BA220SN1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing} }$ 

"#" indicates a package specification code.

Note: This datasheet may be out of date

## BLM18BA220SN1#

# Specifications

Shape	SMD
Size Code (in mm)	1608
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Impedance (at 100MHz)	22Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	500mA
Rated Current (at 125°C)	500mA
DC Resistance(max.)	0.35Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1

2 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2018/06/06


<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.


Note: This datasheet may be out of date.  $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM18BA220SN1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing} }$ Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=BLM18BA220SN1%23

## BLM18BA220SN1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.